

This Manual is provided by
CBTricks.com

Someone who wanted to help you repair your equipment put together this information.

Cobra150GTL DX Parts List

If you would like to help us put more manuals online support us.

Preliminary Information (There will be updates)

If you would like to help with this project let us know.

Supporters of CBTricks.com paid for the hosting so you would have this file.

CBTricks.com is a non-commercial personal website was created to help promote the exchange of service, modification, technically oriented information, and historical information aimed at the Citizens Band, GMRS (CB "A" Band), MURS, Amateur Radios and RF Amps.

CBTricks.com is not sponsored by or connected to any Retailer, Radio, Antenna Manufacturer or Amp Manufacturer, or affiliated with any site links shown in the links database. The use of product or company names on my web site is not endorsement of that product or company.

If your company would like to provide technical information to be featured on this site I will put up on the site as long as I can do it in a non-commercial way.

The site is supported with donation from users, friends and selling of the Galaxy Service Manual CD to cover some of the costs of having this website on the Internet instead of relying on banner ads, pop-up ads, commercial links, etc. Thus I do not accept advertising banners or pop-up/pop-under advertising or other marketing/sales links or gimmicks on my website.

ALL the money from donations is used for CBTricks.com I didn't do all the work to make money (I have a day job). This work was not done for someone else to make money also, for example the ebay CD sellers.

All Trademarks, Logos, and Brand Names are the property of their respective owners.
This information is not provided by, or affiliated in any way with any radio or antenna Manufacturers.

Thank you for any support you can give.

Cobra 150GTL DX

AMR-00001-COA COVER ASSY

REF #	Description	Part #
	SCREW (+)MACHINE(BH) M3.0x6 Ni-PLATING	614-00001-AA
	SCREW FH(+)MACHINE SCREW M3.0x8.0	640-00017-AA
	NUT M3.0x2.4 Zn-PLAT	650-00006-AA
	WASHER D:Ø8.0, d=Ø3.2 T=0.6	660-00007-AA
	TOP COVER EGI BLACK VINYL COATING T=1.0	710-00001-AA
	BOTTOM COVER EGI BLACK VINYL COATING T=1.0	710-00002-AA
	ESCUTCHEON ABS 94HB NATURAL CR PLATING	800-00002-AA
	VOLUME KNOB A ABS 94HB NATURAL CR PLATING	830-00093-AA
	VOLUME KNOB B ABS 94HB NATURAL CR PLATING	830-00094-AA
	VOLUME KNOB MODE ABS 94HB NATURAL CR PLATING	830-00095-AA
	ROTARY KNOB ABS 94HB NATURAL CR PLATING	830-00096-AA
	FELT SPKFELT SPK 90x0x90.0 T=0.15 BLACK	901-00024-AB
	FELT FELT 30.0x8.0 T=0.5	901-00025-AA
	FELT 190.0x64.0 T=0.12	901-00030-AA
	FELT 190.0x10.0 T=0.5	901-00031-AA
	OVERLAY PVC T=0.3	911-00028-AA
	POLY BAG P.E 200x300 T=0.05	932-00300-DA
	PAD DW1S T=7.5 680x70	942-00062-AA

AMR-00001-MBA BODY ASSY

REF #	Description	Part #
	SCREW (+)MACHINE(PH)M2.6x4 Zn-PLATING	613-00005-AA
	SCREW (+)MACHINE(BH) M3.0x4 Zn-PLATING	614-00003-AA
	SCREW (+)MACHINE M3.0x8(PH) Zn BLACK	614-00008-AA
	SCREW (+)MACHINE M3.0x12(PH) Ni PLATING	614-00009-AA
	SCREW (+)MACHINE(BH) M3.0x7 ZN PLATING	614-00010-AA
	SCREW TAPPING(BH) M3.0x6.0 Zn PLATING	624-00002-AA
	SCREW TAPPING(PH) M3x4.0 ZN PLATING	624-00005-AA
	NUT M3.0x2.4 Zn-PLAT	650-00006-AA
	WASHER D:Ø8.0, d=Ø3.2 T=0.6	660-00007-AA
	BUSHING NYLON + GLASS Ø6.0	661-00003-AA
	BUSHING Ø6.0	661-00004-AA
	MICA MICA PLATE T=0.3	663-00001-AA
	MICA 21.0x18.5 T=0.3	663-00002-AA
	FRONT FRAME EGI US COATING T=1.0	700-00009-AA
	SIDE FRAME(L) AL T=2.0	700-00011-AA
	SIDE FRAME(R) AL T=2.0	700-00012-AA
	MIC BRACKET SPC T=1.0 NI PLATE	740-00008-AA
	RUG TERMINAL SPT L=20 T=0.3	750-00104-AA
	RUG TERMINAL SPT L=11 T=0.3	750-00105-AA
	HEAT SINK AL ANODIZING COATING	760-00003-AA
	EL SHIELD CAN SPT T=0.3	770-00090-AA
	CORD STOPPER PP	884-00009-AA
	FELT Ø20 T=0.5	901-00027-AA
	BENDING WIRE L=50.0	902-00020-AA
	INSULATION PAPER PAPER T=0.18 90.0x23.0	910-00021-AA
	DOUBLE SIDE SPONGE 10.0x5.0 T=2.0	920-00095-AA
	NAME LABEL POLYESTER STICKER T=0.09	990-00478-AA

Cobra 150GTL DX

AMR-00001-MCA MIC ASSY

REF #	Description	Part #
	SCREW TAPPING(PH) M3.0x8.0 BLACK	624-00001-AA
	PLUS SCREW (+)PLUS(PH) M2.6x6.0 BLACK	642-00003-AA
	WASHER D:Ø8.0, d=Ø3.2 T=0.6	660-00007-AA
	GRILL STEEL Ø0.5 Zn PLATING	780-00027-AA
	UPPER COVER MIC ABS 94HB BLACK #400	810-00261-AA
	BOTTOM COVER MIC ABS 94HB BLACK #400	810-00262-AA
	HOUSING ABS 94HB #400 BLACK	812-00010-AA
	SWITCH HOUSING ABS 94HB #400 BLACK	812-00011-AA
	LEVER ABS 94HB BLACK #400	840-00009-AA
	HANGER ABS 94HB BLACK #400	870-00030-AA
	MIC TUBE PVC HOSE CLEAR D:7.0 d:6.0 L=30mm	884-00002-AA
	FELT MIC 79.8x62.3 T=0.3 BLACK	901-00022-AB
	SILICONE BOND CEMEDINE SUPER X NO.8008 BLACK(g)	991-00002-AA
	MIC DYNAMIC DM-3516	MCN-52WDF-AA
	CONNECTER HEADER PLUG TCK-16-4(P)	NCH-04HD1-TA
	PUSH SWITCH(MIC PTT) SKPS-2210C	SPU-2210C-SA
	WIRE AWG24 3-7 BLACK 70	WI2-4B070-MA
	CURL CORD 370mm & BUSHING	WP0-6B370-FA
	CONNECTER SOCKET MIC TCN-16-4R(PCB)	NCS-04HD1-TB

AMR-00001-MM3 PCB MANUAL 3 ASSY

REF #	Description	Part #
SW3	SLIDE SWITCH SKS-3201C	SSL-3201V-SA
SW7	SLIDE SWITCH SKS-3301C	SSL-3301V-SA
SW9	SLIDE SWITCH SKS-3301C	SSL-3301V-SA
SW14	SLIDE SWITCH SKS-3201C	SSL-3201V-SA
MET1	METER P210F	ZME-P210F-VA
DIS1	LED DISPLAY LDD40TSR-10 (SUPER RED)	AEP-040TR-VA
	LENS ACRYL CLEAR(RED)	850-00101-AA
LED1	LED,GN/RD,3mm,LEAD LTL-1BEHJ 3mm,GN/RD	AMN-00001-AA
LED2	PILOT LAMP 30 14V 40mA	AMP-00002-AA
LED3	LED LAMP LI2840 & 3 RED	AMN-12840-BA

AMR-00001-MM4 PCB 4 ASSY

REF #	Description	Part #
VR3	VARIABLE RESISTER TPNN1255-30SP-R1:B10K, R2:B5K	RVB-103AM-MA
VR101	VARIABLE RESISTER TPNN1255-30SP-R1:B50K, R2:A50K	RVB-503AM-MB
VR103	VARIABLE RESISTER TPNN1251-30SP-R1:B50K, R2:B5K	RVB-503AM-MC
VR107	VARIABLE RESISTER TPNN1251-30SP-R1:B5K, R2:10K	RVB-103AM-MC

AMR-00001-MM5 PCB 5 ASSY

REF #	Description	Part #
	PCB MAIN 234x186.8x1.6(T) 1/1 HALL	PFM-0089F-BA
SW4	SWITCH ROTARY TRS2401-15SP(2C-4P)	SRO-2415H-TA
SW11	SWITCH ROTARY TRS2301-15SP(2C-3P)	SRO-2315H-TA

AMR-00001-MM6 CH. Sel. PCB MANUAL 6 ASSY

REF #	Description	Part #
	PCB MAIN 234x186.8x1.6(T) 1/1 HALL	PFM-0089G-BA
SW1	PULSE SWITCH TRS1301-20SP	SPL-T1301-TA

Cobra 150GTL DX

AMR-00001-MS8 EL Driver PCB 8 ASSY

REF #	Description	Part #
L8	COIL CHOKE 1mH	BCH-102UK-FA

REF #	Description	Part #
C20	CHIP CERAMIC 1608 100pF	C16-101ZJ-AB
C254	ELECT CAPACITOR RMS16V 100uF 5x11	CEF-101ZM-GC
C260	CHIP CERAMIC 1608 100pF	C16-101ZJ-AB
C261	ELECT CAPACITOR RMS16V 100uF 5x11	CEF-101ZM-GC
C264	CHIP TANTALUM 10uF 16V	CTC-100AM-FA
C266	ELECT CAPACITOR RMS16V 470uF 8x11.5	CEF-471ZM-GA
C270	MYLAR CAPACITOR 683PF 100V	CMB-683ZJ-PA
C275	CHIP CERAMIC 1608 100pF	C16-101ZJ-AB
C280	CHIP TANTALUM 10uF 16V	CTC-100AM-FA
C289	CHIP TANTALUM 10uF 16V	CTC-100AM-FA

REF #	Description	Part #
D4	DIODE ZENER CHIP KDZ5.1EV USM	DZC-5115E-AA
D57	DIODE KDS160	DSC-S160S-AA
D61	DIODE KDS160	DSC-S160S-AA

REF #	Description	Part #
IC9	IC HIGH VOLTAGE EL LAMP DRIVER HV823	IEL-HV823-DA
IC12	IC REGULATOR KIA7805AF(D-PAK)	IRG-7805D-KB

REF #	Description	Part #
R198	FILM CHIP RESISTOR 470	R16-471AJ-AA
R237	FILM CHIP RESISTOR 10	R16-100AJ-AA
R300	FILM CHIP RESISTOR 1.8M	R16-185AJ-AA
R301	FILM CHIP RESISTOR 10	R16-100AJ-AA
R308	FILM CHIP RESISTOR 1K	R16-102AJ-AA
R310	FILM CHIP RESISTOR 1K	R16-102AJ-AA
R320	FILM CHIP RESISTOR 10	R16-100AJ-AA
R330	FILM CHIP RESISTOR 2.7K	R16-272AJ-AA
R334	FILM CHIP RESISTOR 2.7K	R16-272AJ-AA
R336	FILM CHIP RESISTOR 1K	R16-102AJ-AA
R337	FILM CHIP RESISTOR 470	R16-471AJ-AA
R338	FILM CHIP RESISTOR 8.2K	R16-822AJ-AA
R339	FILM CHIP RESISTOR 47K	R16-473AJ-AA
R240	FILM CHIP RESISTOR 560	R16-561AJ-AA
R241	FILM CHIP RESISTOR 560	R16-561AJ-AA
R261	FILM CHIP RESISTOR 560K	R16-564AJ-AA

REF #	Description	Part #
T1	TRANSISTOR KTC3875Y	TRC-3875Y-AA
Q45	TRANSISTOR EPITAXIAL PLANAR NPN KTC4377(SOT-89)	TRC-4377C-AA
Q48	TRANSISTOR EPITAXIAL PLANAR NPN KTC4377(SOT-89)	TRC-4377C-AA

Cobra 150GTL DX

AMR-00001-MPM MAIN PCB MANUAL ASSY

REF #	Description	Part #
BF1	BEAD 3.5x0.8x6T	BBA-35086-SA
BF3	BEAD 3.5x0.8x6T	BBA-35086-SA
BF6	BEAD 3.5x0.8x6T	BBA-35086-SA
L2	AXIAL LEAD INDUCTOR AL03TO6R8K	BAC-068UK-AA
L13	COIL PEAKING 1.0uH LEAD TYPE	BCP-00100-FA
L14	COIL PEAKING 1.0uH LEAD TYPE	BCP-00100-FA
L15	COIL PEAKING 1.0uH LEAD TYPE	BCP-00100-FA
L16	COIL SPRING ST03 6TR 4PIE 5 0.8 H TYPE	BSC-H060C-AH
L18	COIL SPRING ST03 6TR 4PIE 5 0.8 H TYPE	BSC-H060C-AH
L21	COIL TANK SK02 25.2MHz 0.15uH	BCT-00015-FA
L22	COIL SPRING ST06 5.5TR 6PIE 5 0.8 H TYPE	BSC-H055C-AH
L24	COIL SPRING ST04 6.5TR 6PIE 5 0.8 H TYPE	BSC-H065C-AH
L230	COIL SPRING ST04 6.5TR 6PIE 5 0.8 H TYPE	BSC-H065C-AH
L231	COIL SPRING ST06 5.5TR 6PIE 5 0.8 H TYPE	BSC-H055C-AH
T701	COIL IFT LB101(10.7MHz) 51PF	BFA-LB101-FA
T702	COIL IFT LB045(FM DET 4.5MHz +/-4% 100pF	BFA-LB045-FA
T703	COIL IFT LB280(27.0MHz)	BFA-LB280-FA
T704	COIL IFT LB282(27.0MHz) 24PF	BFA-LB282-FA
T705	COIL IFT LB282(27.0MHz) 24PF	BFA-LB282-FA
T706	COIL IFT LB282(27.0MHz) 24PF	BFA-LB282-FA
T707	COIL IFT LB101(10.7MHz) 51PF	BFA-LB101-FA
T708	COIL IFT LB101(10.7MHz) 51PF	BFA-LB101-FA
T710	COIL IFT 3201545(455KHz/7mm)	BFA-71545-AA
T712	COIL IFT LB160(16.5MHz) 47PF	BFA-LB160-FA
T713	COIL IFT LB161(16.5MHz) 39PF	BFA-LB161-FA
T717	COIL IFT LB161(16.5MHz) 39PF	BFA-LB161-FA
T718	COIL IFT LB283(27.0MHz) 33PF	BFA-LB283-FA
T719	COIL IFT LB106(10.7MHz) 68PF	BFA-LB106-FA
T720	COIL IFT LB283(27.0MHz) 33PF	BFA-LB283-FA
T721	COIL IFT LB284(27.0MHz) 18PF	BFA-LB284-FA
T722	COIL IFT LB284(27.0MHz) 18PF	BFA-LB284-FA
T723	COIL IFT LB280(27.0MHz)	BFA-LB280-FA

REF #	Description	Part #
X1	CRYSTAL 10.240MHz +/- 30PPM HC-49S	XCN-1024A-KC
X3	CRYSTAL 4.194304MHz	XCN-4194A-KA
X4	CRYSTAL 10.695MHz +/-20PPM HC49S	XCN-1069A-KA

REF #	Description	Part #
CF3	FILTER CERAMIC LT455HTW	FCN-455A5-CB
	10.695MHz 10L08B 49T MCF	FXN-106BP-KA

REF #	Description	Part #
TF1	POWER TRANS TF1-15	EPW-TF115-AA

REF #	Description	Part #
	EL BACK LIGHT PH3491RGEN(REDF GREEN)	AEL-3491R-AA

Cobra 150GTL DX

REF #	Description	Part #
Q1	TRANSISTOR KTC3875Y	TRC-3875Y-AA
Q2	TRANSISTOR EPTAXAL PLANAR PNP KTA200	TRA-2000F-AA
Q3	TRANSISTOR KTC3880S-Y	TRC-3880Y-AA
Q4	TRANSISTOR KTC3880S-Y	TRC-3880Y-AA
Q5	TRANSISTOR KTK211Y(SOT-23)	TRC-K211S-AA
Q6	TRANSISTOR KTA1504GR	TRA-1504G-AA
Q7	TRANSISTOR KTC3880S-Y	TRC-3880Y-AA
Q8	TRANSISTOR BRT KRA101S	TRR-A101S-AA
Q9	TRANSISTOR BRT KRC111S	TRR-C111S-AA
Q10	TRANSISTOR KTC3875Y	TRC-3875Y-AA
Q11	TRANSISTOR KTK211Y(SOT-23)	TRC-K211S-AA
Q12	TRANSISTOR KTC3880S-Y	TRC-3880Y-AA
Q13	TRANSISTOR KTC3875Y	TRC-3875Y-AA
Q14	TRANSISTOR EPTAXAL PLANAR PNP	TRA-2000F-AA
Q17	TRANSISTOR KTC3875Y	TRC-3875Y-AA
Q18	TRANSISTOR KTC3880S-Y	TRC-3880Y-AA
Q19	TRANSISTOR KTC3880S-Y	TRC-3880Y-AA
Q22	TRANSISTOR KTC3880S-Y	TRC-3880Y-AA
Q25	TRANSISTOR BRT KRC111S	TRR-C111S-AA
Q26	TRANSISTOR KTC3875Y	TRC-3875Y-AA
Q28	TRANSISTOR KTC3875Y	TRC-3875Y-AA
Q31	TRANSISTOR KTA1504GR	TRA-1504G-AA
Q32	TRANSISTOR BRT KRC111S	TRR-C111S-AA
Q36	TRANSISTOR KTC3880S-Y	TRC-3880Y-AA
Q37	TRANSISTOR KTC3880S-Y	TRC-3880Y-AA
Q38	TRANSISTOR KTC3880S-Y	TRC-3880Y-AA
Q39	TRANSISTOR BRT KRC111S	TRR-C111S-AA
Q42	TRANSISTOR BRT KRA102S	TRR-A102S-AA
Q43	TRANSISTOR KTA1504GR	TRA-1504G-AA
Q44	TRANSISTOR KTC3875Y	TRC-3875Y-AA
Q46	TRANSISTOR KTC3880S-Y	TRC-3880Y-AA
Q53	TRANSISTOR KTC3880S-Y	TRC-3880Y-AA
Q55	TRANSISTOR BRT KRC102S	TRR-C102S-AA
Q57	TRANSISTOR BRT KRC102S	TRR-C102S-AA
Q59	TRANSISTOR BRT KRC111S	TRR-C111S-AA
Q64	TRANSISTOR KTC3875Y	TRC-3875Y-AA
Q65	TRANSISTOR KTB1370	TRB-1370T-AA
Q66	TRANSISTOR KTA1001(SOT-89)	TRA-1001Y-AA
Q68	TRANSISTOR KTC3875Y	TRC-3875Y-AA
Q69	TRANSISTOR KTC3880S-Y	TRC-3880Y-AA
Q71	TRANSISTOR 2SC2314	TRC-2314T-SA
Q72	TRANSISTOR RD06HHF1(30MHz,6W)	TRD-06HHF-CA
Q73	TRANSISTOR RD16HHF1(30MHz,16W)	TRD-16HHF-CA
Q74	TRANSISTOR RD16HHF1(30MHz,16W)	TRD-16HHF-CA
Q75	TRANSISTOR KTC3880S-Y	TRC-3880Y-AA
Q79	TRANSISTOR BRT KRC111S	TRR-C111S-AA
Q80	TRANSISTOR BRT KRC111S	TRR-C111S-AA
Q81	TRANSISTOR KTA1504GR	TRA-1504G-AA

Cobra 150GTL DX

REF #	Description	Part #
IC1	IC FM IF UTC3361B	IFI-3361A-CA
IC2	IC OP AMP IL324D	IOA-324DA-EA
IC4	IC BIPOLAR KIA4558F	IOA-4558A-KA
IC5	IC REGULATOR KIA78L05F	IRG-7805F-KA
IC6	IC EEPROM HT24LC02	IEE-24C02-HA
IC7	IC PLL LC7152(MFP24S)	IPL-7152C-SA
IC8	IC CPU TMP87CM21CDF(6CH8)150/200GTL	ICP-8721P-AA
IC9	IC IN74HC164AD	ICP-7416F-VA
IC9	IC AUDIO AMP TDA2003V	IAD-2003A-SA
IC11	IC AUDIO AMP TDA2005	IAD-2005A-SA
IC10	IC REGULATOR KIA7808AP/API(TO-2201S)	IRG-7808A-KA
IC12	IC IN74HC164AD	ICP-7416F-VA
IC25	IC REGULATOR KIA78L05F	IRG-7805F-KA
IC26	IC BIPOLAR KIA6058F(FLP-8)	IFE-6058D-KA
IC501	IC BIPOLAR KIA4558F	IOA-4558A-KA
IC502	IC VOICE ECHO HT8970(SOP16)	IVS-8970C-HA

REF #	Description	Part #
D2	DIODE RECTIFIER 1N60P GERMANIUM	DRB-1N60D-CA
D6	DIODE KDS160	DSC-S160S-AA
D7	DIODE SCHOTTY RB706F	DHC-RB706-AA
D11	DIODE Si CHIP KDS226	DIC-S226S-AA
D12	DIODE VARICAP CHIP KDV251S-C-RTK Q3C	DVC-251CS-AB
D13	DIODE VARICAP CHIP KDV251S-C-RTK Q3C	DVC-251CS-AB
D14	DIODE VARICAP CHIP KDV251S-C-RTK Q3C	DVC-251CS-AB
D17	DIODE VARICAP CHIP KDV251S-C-RTK Q3C	DVC-251CS-AB
D18	DIODE Si CHIP KDS184S	DIC-S184S-AA
D20	DIODE RECTIFIER 1N60P GERMANIUM	DRB-1N60D-CA
D21	DIODE Si CHIP KDS181S	DIC-S181S-AA
D22	DIODE KDS160	DSC-S160S-AA
D23	DIODE Si CHIP KDS184S	DIC-S184S-AA
D24	DIODE SCHOTTY RB706F	DHC-RB706-AA
D25	DIODE KDS160	DSC-S160S-AA
D27	DIODE KDS160	DSC-S160S-AA
D28	DIODE KDS160	DSC-S160S-AA
D30	DIODE VARICAP CHIP KDV251S-C-RTK Q3C	DVC-251CS-AB
D31	DIODE VARICAP CHIP KDV251S-C-RTK Q3C	DVC-251CS-AB
D33	DIODE Si CHIP KDS184S	DIC-S184S-AA
D34	DIODE Si CHIP KDS226	DIC-S226S-AA
D37	DIODE Si CHIP KDS181S	DIC-S181S-AA
D39	DIODE KDS160	DSC-S160S-AA
D48	DIODE RECTIFIER 6A6(600V6A)	DRF-6A06P-MA
D62	DIODE Si CHIP KDS184S	DIC-S184S-AA
D68	DIODE VARICAP CHIP KDV251S-C-RTK Q3C	DVC-251CS-AB
D69	DIODE VARICAP CHIP KDV251S-C-RTK Q3C	DVC-251CS-AB
D71	DIODE VARICAP CHIP KDV251S-C-RTK Q3C	DVC-251CS-AB
D72	DIODE VARICAP CHIP KDV251S-C-RTK Q3C	DVC-251CS-AB
D73	DIODE KDS160	DSC-S160S-AA
D74	DIODE KDS160	DSC-S160S-AA
D75	DIODE Si CHIP KDS184S	DIC-S184S-AA
D77	DIODE KDS160	DSC-S160S-AA
D78	DIODE Si CHIP KDS184S	DIC-S184S-AA
D79	DIODE ZENER CHIP Z02W6.8V Y	DZC-6820S-AB

Cobra 150GTL DX

REF #	Description	Part #
CT1	TRIMMER 20P RED	CRB-200ZI-PA
CT2	TRIMMER 20P RED	CRB-200ZI-PA

REF #	Description	Part #
C1	CHIP CERAMIC 1608 0.022uF	C16-223ZK-AB
C2	ELECT CAPACITOR RMS16V 22uF 5x11	CEF-220ZM-GA
C3	CHIP CERAMIC 1608 10pF	C16-100ZD-AB
C4	CHIP CERAMIC 1608 22pF	C16-220ZJ-AB
C5	CHIP CERAMIC 1608 0.0047uF	C16-472ZK-AB
C5	CHIP CERAMIC 1608 0.0047uF	C16-472ZK-AB
C6	CHIP CERAMIC 1608 0.001uF	C16-102ZK-AB
C7	CHIP CERAMIC 1608 0.001uF	C16-102ZK-AB
C8	CHIP CERAMIC 1608 0.01uF	C16-103ZK-AB
C9	CHIP CERAMIC 1608 0.01uF	C16-103ZK-AB
C10	ELECT CAPACITOR 10uF 16V 5x11	CEF-100ZM-GB
C11	CHIP CERAMIC 1608 0.022uF	C16-223ZK-AB
C12	ELECT CAPACITOR 33uF 16V 5x11	CEF-330ZM-GB
C13	ELECT CAPACITOR 33uF 16V 5x11	CEF-330ZM-GB
C14	CHIP CERAMIC 1608 0.047uF	C16-473ZK-AB
C15	ELECT CAPACITOR RMS16V 100uF 5x11	CEF-101ZM-GC
C18	CHIP CERAMIC 1608 0.1uF	C16-104ZZ-AB
C19	CHIP CERAMIC 1608 0.1uF	C16-104ZZ-AB
C20	CHIP CERAMIC 1608 0.01uF	C16-103ZK-AB
C21	CONDENSER CERAMIC DISK 0.1uF	CDB-104ZK-PA
C22	CHIP CERAMIC 1608 0.01uF	C16-103ZK-AB
C23	ELECT CAPACITOR RMS16V 22uF 5x11	CEF-220ZM-GA
C24	CHIP CERAMIC 1608 0.047uF	C16-473ZK-AB
C26	CHIP CERAMIC 1608 0.01uF	C16-103ZK-AB
C27	CHIP CERAMIC 1608 0.022uF	C16-223ZK-AB
C28	CHIP CERAMIC 1608 22pF	C16-220ZJ-AB
C29	CHIP CERAMIC 1608 0.047uF	C16-473ZK-AB
C30	CHIP CERAMIC 1608 470pF	C16-471ZK-AB
C31	CHIP CERAMIC 1608 0.1uF	C16-104ZZ-AB
C32	CONDENSER CERAMIC DISK 0.1uF	CDB-104ZK-PA
C33	CHIP CERAMIC 1608 220pF	C16-221ZJ-AB
C34	CHIP CERAMIC 1608 0.022uF	C16-223ZK-AB
C35	CHIP CERAMIC 1608 0.1uF	C16-104ZZ-AB
C36	CHIP CERAMIC 1608 0.1uF	C16-104ZZ-AB
C37	ELECT CAPACITOR RMS16V 47uF 5x11	CEF-470ZM-GA
C38	CONDENSER CERAMIC DISK 18PF	CDB-180ZJ-PA
C39	CHIP CERAMIC 1608 22pF	C16-220ZJ-AB
C40	CHIP CERAMIC 1608 0.01uF	C16-103ZK-AB
C41	ELECT CAPACITOR RMS16V 47uF 5x11	CEF-470ZM-GA
C42	CHIP CERAMIC 1608 0.22uF	C16-224ZZ-AB
C43	CHIP CERAMIC 1608 0.022uF	C16-223ZK-AB
C44	CHIP CERAMIC 1608 0.0047uF	C16-472ZK-AB
C46	CHIP CERAMIC 1608 0.1uF	C16-104ZZ-AB
C47	ELECT CAPACITOR RMS16V 1000uF 10x16	CEF-102ZM-GA
C48	ELECT CAPACITOR RMS25V 1000uF 10x20	CEF-102ZM-GC
C49	ELECT CAPACITOR RMS16V 100uF 5x11	CEF-101ZM-GC

Cobra 150GTL DX

REF #	Description	Part #
C51	CHIP CERAMIC 1608 0.0047uF	C16-472ZK-AB
C52	CHIP CERAMIC 1608 0.0047uF	C16-472ZK-AB
C53	CHIP CERAMIC 1608 0.0047uF	C16-472ZK-AB
C54	CHIP CERAMIC 1608 0.01uF	C16-103ZK-AB
C55	CHIP CERAMIC 1608 82PF	C16-820ZK-AB
C56	CHIP CERAMIC 1608 0.01uF	C16-103ZK-AB
C57	CHIP CERAMIC 1608 0.047uF	C16-473ZK-AB
C58	CHIP CERAMIC 1608 0.01uF	C16-103ZK-AB
C59	CHIP CERAMIC 1608 0.01uF	C16-103ZK-AB
C60	CHIP CERAMIC 1608 0.012uF	C16-123ZK-AB
C61	CHIP CERAMIC 1608 82PF	C16-820ZK-AB
C62	CHIP CERAMIC 1608 2pF	C16-020ZC-AC
C63	CHIP CERAMIC 1608 82PF	C16-820ZK-AB
C64	CHIP CERAMIC 1608 0.01uF	C16-103ZK-AB
C65	CHIP CERAMIC 1608 3pF	C16-030ZC-AB
C66	CHIP CERAMIC 1608 0.01uF	C16-103ZK-AB
C67	CHIP CERAMIC 1608 0.01uF	C16-103ZK-AB
C69	CHIP CERAMIC 1608 2pF	C16-020ZC-AC
C71	CHIP CERAMIC 1608 82PF	C16-820ZK-AB
C72	CHIP CERAMIC 1608 0.001UF	C16-102ZK-AB
C73	CHIP CERAMIC 1608 7pF	C16-070ZC-AB
C74	CHIP CERAMIC 1608 0.001UF	C16-102ZK-AB
C82	CHIP CERAMIC 1608 0.01uF	C16-103ZK-AB
C84	CHIP CERAMIC 1608 0.047uF	C16-473ZK-AB
C85	ELECT CAPACITOR RMS16V 47uF 5x11	CEF-470ZM-GA
C86	CHIP CERAMIC 1608 0.047uF	C16-473ZK-AB
C87	CHIP CERAMIC 1608 0.047uF	C16-473ZK-AB
C88	CHIP CERAMIC 1608 0.001UF	C16-102ZK-AB
C89	CHIP CERAMIC 1608 470pF	C16-471ZK-AB
C91	ELECT CAPACITOR 1uF 50V 5x11	CEF-010ZM-GB
C92	CHIP CERAMIC 1608 0.001UF	C16-102ZK-AB
C94	CHIP CERAMIC 1608 0.01uF	C16-103ZK-AB
C97	CHIP CERAMIC 1608 100pF	C16-101ZJ-AB
C98	CHIP CERAMIC 1608 0.01uF	C16-103ZK-AB
C101	CHIP CERAMIC 1608 33pF	C16-330ZJ-AB
C103	CONDENSER CERAMIC DISK 27PF +/-5% 50V CH	CDB-270ZK-PB
C106	CHIP CERAMIC 1608 0.001UF	C16-102ZK-AB
C107	CHIP CERAMIC 1608 0.01uF	C16-103ZK-AB
C109	CHIP CERAMIC 1608 82PF	C16-820ZK-AB
C110	CHIP CERAMIC 1608 100pF	C16-101ZJ-AB
C112	CHIP CERAMIC 1608 220pF	C16-221ZJ-AB
C113	CHIP CERAMIC 1608 3pF	C16-030ZC-AB
C115	CHIP CERAMIC 1608 0.01uF	C16-103ZK-AB
C116	ELECT CAPACITOR 4.7uF 50V 5x11	CEF-047ZM-GB
C117	CHIP CERAMIC 1608 47pF	C16-470ZJ-AB
C118	CHIP CERAMIC 1608 22pF	C16-220ZJ-AB
C119	CHIP CERAMIC 1608 0.01uF	C16-103ZK-AB
C122	CHIP CERAMIC 1608 22pF	C16-220ZJ-AB
C123	CHIP CERAMIC 1608 470pF	C16-471ZK-AB
C126	CHIP CERAMIC 1608 10pF	C16-100ZD-AB
C127	CHIP CERAMIC 1608 390PF	C16-391ZJ-AB
C128	CHIP CERAMIC 1608 0.047uF	C16-473ZK-AB

Cobra 150GTL DX

REF #	Description	Part #
C129	CHIP CERAMIC 1608 4pF	C16-040ZC-AB
C130	CHIP CERAMIC 1608 0.01uF	C16-103ZK-AB
C132	ELECT CAPACITOR 220uF 16V 20% 6.3x11	CEF-221ZM-GC
C133	CHIP CERAMIC 1608 0.01uF	C16-103ZK-AB
C135	CHIP CERAMIC 1608 0.001UF	C16-102ZK-AB
C137	CHIP CERAMIC 1608 0.022uF	C16-223ZK-AB
C138	ELECT CAPACITOR 10uF 16V 5x11	CEF-100ZM-GB
C144	ELECT CAPACITOR 220uF 16V 20% 6.3x11	CEF-221ZM-GC
C145	CHIP CERAMIC 1608 0.047uF	C16-473ZK-AB
C146	ELECT CAPACITOR 2.2uF 50V 5x11	CEF-022ZM-GB
C147	ELECT CAPACITOR 4.7uF 50V 5x11	CEF-047ZM-GB
C148	CHIP CERAMIC 1608 0.001UF	C16-102ZK-AB
C149	CHIP CERAMIC 1608 0.47uF	C16-474ZZ-AB
C150	CHIP CERAMIC 1608 6pF	C16-060ZC-AB
C151	CHIP CERAMIC 1608 0.01uF	C16-103ZK-AB
C152	CHIP CERAMIC 1608 0.001UF	C16-102ZK-AB
C153	CHIP CERAMIC 1608 0.001UF	C16-102ZK-AB
C154	CHIP CERAMIC 1608 220pF	C16-221ZJ-AB
C155	ELECT CAPACITOR 2.2uF 50V 5x11	CEF-022ZM-GB
C159	CHIP CERAMIC 1608 0.01uF	C16-103ZK-AB
C160	CHIP CERAMIC 1608 0.047uF	C16-473ZK-AB
C161	CHIP CERAMIC 1608 0.1uF	C16-104ZZ-AB
C162	CHIP CERAMIC 1608 0.047uF	C16-473ZK-AB
C164	CHIP CERAMIC 1608 0.01uF	C16-103ZK-AB
C169	CHIP CERAMIC 1608 0.001UF	C16-102ZK-AB
C171	CHIP CERAMIC 1608 0.001UF	C16-102ZK-AB
C173	CHIP CERAMIC 1608 0.01uF	C16-103ZK-AB
C174	CONDENSER CERAMIC DISK 0.1uF	CDB-104ZK-PA
C175	ELECT CAPACITOR 10uF 16V 5x11	CEF-100ZM-GB
C176	CHIP CERAMIC 1608 100pF	C16-101ZJ-AB
C177	CHIP CERAMIC 1608 0.047uF	C16-473ZK-AB
C178	CHIP CERAMIC 1608 0.01uF	C16-103ZK-AB
C179	CHIP CERAMIC 1608 0.01uF	C16-103ZK-AB
C180	CHIP CERAMIC 1608 10pF	C16-100ZD-AB
C181	CONDENSER CERAMIC DISK 0.01uF	CDB-103ZK-PA
C183	ELECT CAPACITOR RMS16V 47uF 5x11	CEF-470ZM-GA
C185	CHIP CERAMIC 1608 0.1uF	C16-104ZZ-AB
C186	ELECT CAPACITOR 2.2uF 50V 5x11	CEF-022ZM-GB
C188	CHIP CERAMIC 1608 0.01uF	C16-103ZK-AB
C189	ELECT CAPACITOR RMS16V 100uF 5x11	CEF-101ZM-GC
C191	CHIP CERAMIC 1608 0.047uF	C16-473ZK-AB
C192	ELECT CAPACITOR RMS16V 47uF 5x11	CEF-470ZM-GA
C193	CHIP CERAMIC 1608 0.01uF	C16-103ZK-AB
C196	CHIP CERAMIC 1608 0.047uF	C16-473ZK-AB
C197	CHIP CERAMIC 1608 0.022uF	C16-223ZK-AB
C198	CHIP CERAMIC 1608 0.01uF	C16-103ZK-AB
C199	CHIP CERAMIC 1608 0.01uF	C16-103ZK-AB
C200	CHIP CERAMIC 1608 0.01uF	C16-103ZK-AB
C201	CHIP CERAMIC 1608 0.01uF	C16-103ZK-AB
C202	ELECT CAPACITOR RMS16V 47uF 5x11	CEF-470ZM-GA
C203	CHIP CERAMIC 1608 0.01uF	C16-103ZK-AB
C204	CHIP CERAMIC 1608 0.047uF	C16-473ZK-AB
C208	CHIP CERAMIC 1608 27pF	C16-270ZJ-AB

Cobra 150GTL DX

REF #	Description	Part #
C209	CHIP CERAMIC 1608 33pF	C16-330ZJ-AB
C211	ELECT CAPACITOR 2.2uF 50V 5x11	CEF-022ZM-GB
C212	CHIP CERAMIC 1608 0.01uF	C16-103ZK-AB
C213	CHIP CERAMIC 1608 220pF	C16-221ZJ-AB
C214	CHIP CERAMIC 1608 22pF	C16-220ZJ-AB
C215	CHIP CERAMIC 1608 270pF	C16-271ZK-AB
C216	ELECT CAPACITOR RMS16V 47uF 5x11	CEF-470ZM-GA
C222	CHIP CERAMIC 1608 27pF	C16-270ZJ-AB
C225	CHIP CERAMIC 1608 0.047uF	C16-473ZK-AB
C226	CHIP CERAMIC 1608 0.047uF	C16-473ZK-AB
C227	ELECT CAPACITOR RMS16V 470uF 8x11.5	CEF-471ZM-GA
C228	ELECT CAPACITOR RMS16V 47uF 5x11	CEF-470ZM-GA
C230	CHIP CERAMIC 1608 56PF	C16-560ZK-AB
C231	CHIP CERAMIC 1608 0.1uF	C16-104ZZ-AB
C233	ELECT CAPACITOR RMS16V 1000uF 10x16	CEF-102ZM-GA
C235	CHIP CERAMIC 1608 0.01uF	C16-103ZK-AB
C236	CONDENSER CERAMIC DISK 0.1uF	CDB-104ZK-PA
C237	CHIP CERAMIC 1608 0.001UF	C16-102ZK-AB
C240	CONDENSER CERAMIC DISK 0.1uF	CDB-104ZK-PA
C243	ELECT CAPACITOR 470uF 50V 20% 10x20	CEF-471ZM-GD
C247	CHIP CERAMIC 1608 0.0047uF	C16-472ZK-AB
C251	CHIP CERAMIC 1608 0.047uF	C16-473ZK-AB
C255	CONDENSER CERAMIC DISK 0.01uF	CDB-103ZK-PA
C256	CONDENSER CERAMIC DISK 0.01uF	CDB-103ZK-PA
C257	CHIP CERAMIC 1608 0.022uF	C16-223ZK-AB
C258	CHIP CERAMIC 1608 0.022uF	C16-223ZK-AB
C263	CHIP CERAMIC 1608 0.047uF	C16-473ZK-AB
C265	CHIP CERAMIC 1608 0.01uF	C16-103ZK-AB
C267	CHIP CERAMIC 1608 0.01uF	C16-103ZK-AB
C268	CHIP CERAMIC 1608 82PF	C16-820ZK-AB
C269	CHIP CERAMIC 1608 2pF	C16-020ZC-AC
C271	CHIP CERAMIC 1608 82PF	C16-820ZK-AB
C272	CHIP CERAMIC 1608 2pF	C16-020ZC-AC
C273	CHIP CERAMIC 1608 82PF	C16-820ZK-AB
C274	CHIP CERAMIC 1608 2pF	C16-020ZC-AC
C277	CHIP CERAMIC 1608 82PF	C16-820ZK-AB
C278	CHIP CERAMIC 1608 220pF	C16-221ZJ-AB
C279	CHIP CERAMIC 1608 100pF	C16-101ZJ-AB
C281	CHIP CERAMIC 1608 0.01uF	C16-103ZK-AB
C282	CHIP CERAMIC 1608 330pF	C16-331ZK-AB
C283	CHIP CERAMIC 1608 0.01uF	C16-103ZK-AB
C284	CHIP CERAMIC 1608 270pF	C16-271ZK-AB
C285	CHIP CERAMIC 1608 0.022uF	C16-223ZK-AB
C287	CONDENSER CERAMIC DISK 0.1uF	CDB-104ZK-PA
C292	ELECT CAPACITOR 1uF 50V 5x11	CEF-010ZM-GB
C297	CONDENSER CERAMIC DISK 220PF +/-5% 50V CH	CDB-221ZK-PB
C299	CONDENSER CERAMIC DISK 220PF +/-5% 50V CH	CDB-221ZK-PB
C302	CONDENSER CERAMIC DISK 150PF +/-5% 50V CH	CDB-151ZK-PB
C303	CONDENSER CERAMIC DISK 0.1uF	CDB-104ZK-PA
C304	ELECT CAPACITOR 1uF 50V 5x11	CEF-010ZM-GB
C305	CONDENSER CERAMIC DISK 560PF +/-5% 50V SL	CDB-561ZK-PB
C306	CONDENSER CERAMIC DISK 560PF +/-5% 50V SL	CDB-561ZK-PB
C307	CONDENSER CERAMIC DISK 22PF	CDB-220ZJ-PA

Cobra 150GTL DX

REF #	Description	Part #
C314	CHIP CERAMIC 1608 1pF	C16-010ZC-AB
C316	ELECT CAPACITOR 1uF 50V 5x11	CEF-010ZM-GB
C317	AB CHIP CERAMIC 1608 0.01uF	C16-103ZK-
C319	CHIP CERAMIC 1608 0.01uF	C16-103ZK-AB
C349	CHIP CERAMIC 1608 100pF	C16-101ZJ-AB
C351	CHIP CERAMIC 1608 0.001UF	C16-102ZK-AB
C352	CHIP CERAMIC 1608 0.047uF	C16-473ZK-AB
C361	CHIP CERAMIC 1608 0.1uF	C16-104ZZ-AB
C362	CHIP CERAMIC 1608 0.1uF	C16-104ZZ-AB
C365	CHIP CERAMIC 1608 0.1uF	C16-104ZZ-AB
C366	ELECT CAPACITOR RMS16V 47uF 5x11	CEF-470ZM-GA
C367	CHIP CERAMIC 1608 100pF	C16-101ZJ-AB
C375	CHIP CERAMIC 1608 0.1uF	C16-104ZZ-AB
C375	CHIP CERAMIC 1608 0.01uF	C16-103ZK-AB
C376	CHIP CERAMIC 1608 0.01uF	C16-103ZK-AB
C377	ELECT CAPACITOR RMS16V 22uF 5x11	CEF-220ZM-GA
C597	CONDENSER CERAMIC DISK 0.1uF	CDB-104ZK-PA
C599	CONDENSER CERAMIC DISK 0.1uF	CDB-104ZK-PA
C603	CONDENSER CERAMIC DISK 0.1uF	CDB-104ZK-PA
C604	CONDENSER CERAMIC DISK 0.1uF	CDB-104ZK-PA
C605	CONDENSER CERAMIC DISK 0.1uF	CDB-104ZK-PA
C606	CONDENSER CERAMIC DISK 0.1uF	CDB-104ZK-PA
C311	CONDENSER CERAMIC DISK 180PF +/-5% 50V CH	CDB-181ZK-PB
C350	ELECT CAPACITOR RMS35V 4.7uF 4x7	CEF-047ZM-GA
C500	ELECT CAPACITOR 4.7uF 50V 5x11	CEF-047ZM-GB
C510	CHIP CERAMIC 1608 0.1uF	C16-104ZZ-AB
C515	CHIP CERAMIC 1608 220pF	C16-221ZJ-AB
C518	CHIP CERAMIC 1608 0.1uF	C16-104ZZ-AB
C520	ELECT CAPACITOR RMS16V 22uF 5x11	CEF-220ZM-GA
C522	ELECT CAPACITOR RMS16V 22uF 5x11	CEF-220ZM-GA
C523	CHIP CERAMIC 1608 0.1uF	C16-104ZZ-AB
C524	ELECT CAPACITOR RMS16V 100uF 5x11	CEF-101ZM-GC
C554	CHIP CERAMIC 1608 0.1uF	C16-104ZZ-AB
C560	ELECT CAPACITOR RMS16V 100uF 5x11	CEF-101ZM-GC
C561	ELECT CAPACITOR 4.7uF 50V 5x11	CEF-047ZM-GB
C564	CHIP CERAMIC 1608 0.1uF	C16-104ZZ-AB
C566	CHIP CERAMIC 1608 0.1uF	C16-104ZZ-AB
C570	CHIP CERAMIC 1608 0.047uF	C16-473ZK-AB
C575	CHIP CERAMIC 1608 0.047uF	C16-473ZK-AB
C576	CHIP CERAMIC 1608 560PF	C16-561ZK-AB
C580	CHIP CERAMIC 1608 0.033uF	C16-333ZK-AB
C589	ELECT CAPACITOR 10uF 16V 5x11	CEF-100ZM-GB
C590	CHIP CERAMIC 1608 560PF	C16-561ZK-AB
C591	ELECT CAPACITOR 4.7uF 50V 5x11	CEF-047ZM-GB
C594	CHIP CERAMIC 1608 0.0056uF	C16-562ZK-AB
C593	ELECT CAPACITOR 10uF 16V 5x11	CEF-100ZM-GB
C607	CHIP CERAMIC 1608 0.01uF	C16-103ZK-AB
C609	CHIP CERAMIC 1608 47pF	C16-470ZJ-AB
C610	CHIP CERAMIC 1608 0.01uF	C16-103ZK-AB
C611	CHIP CERAMIC 1608 0.047uF	C16-473ZK-AB
C614	ELECT CAPACITOR RMS16V 22uF 5x11	CEF-220ZM-GA
C616	CHIP CERAMIC 1608 0.01uF	C16-103ZK-AB
C617	CHIP CERAMIC 1608 220pF	C16-221ZJ-AB
C620	CONDENSER CERAMIC DISK 100PF +/-5% 50V CH	CDB-101ZJ-PB

Cobra 150GTL DX

REF #	Description	Part #
C621	CONDENSER CERAMIC DISK 330PF +/-5% 50V CH	CDB-331ZK-PB
C623	CHIP CERAMIC 1608 560PF	C16-561ZK-AB
C624	CHIP CERAMIC 1608 20pF	C16-200ZJ-AB
C625	CHIP CERAMIC 1608 470pF	C16-471ZK-AB
C627	ELECT CAPACITOR RMS16V 1000uF 10x16	CEF-102ZM-GA
C628	CHIP CERAMIC 1608 0.1uF	C16-104ZZ-AB
C629	CHIP CERAMIC 1608 0.01uF	C16-103ZK-AB
C630	ELECT CAPACITOR 10uF 16V 5x11	CEF-100ZM-GB
C631	ELECT CAPACITOR RMS50V 0.47uF 5x11 50V	CEF-947ZM-GA
C632	ELECT CAPACITOR RMS16V 470uF 8x11.5	CEF-471ZM-GA
C633	ELECT CAPACITOR 10uF 16V 5x11	CEF-100ZM-GB
C634	ELECT CAPACITOR 33uF 16V 5x11	CEF-330ZM-GB
C635	CHIP CERAMIC 1608 0.0022uF	C16-222ZK-AB
C636	CONDENSER CERAMIC DISK 0.1uF	CDB-104ZK-PA
C637	CONDENSER CERAMIC DISK 0.1uF	CDB-104ZK-PA
C638	CONDENSER CERAMIC DISK 0.1uF	CDB-104ZK-PA
C651	ELECT CAPACITOR 10uF 16V 5x11	CEF-100ZM-GB
C652	ELECT CAPACITOR 2.2uF 50V 5x11	CEF-022ZM-GB
C653	ELECT CAPACITOR 2.2uF 50V 5x11	CEF-022ZM-GB
C654	ELECT CAPACITOR 220uF 16V 20% 6.3x11	CEF-221ZM-GC
C655	ELECT CAPACITOR RMS16V 100uF 5x11	CEF-101ZM-GC
C656	CHIP CERAMIC 2012 1uF	C20-105ZZ-AB
C657	CHIP CERAMIC 2012 1uF	C20-105ZZ-AB
C659	ELECT CAPACITOR RMS16V 470uF 8x11.5	CEF-471ZM-GA
C665	ELECT CAPACITOR 220uF 16V 20% 6.3x11	CEF-221ZM-GC
C670	CHIP CERAMIC 1608 0.01uF	C16-103ZK-AB
C676	CHIP CERAMIC 1608 0.001UF	C16-102ZK-AB

REF #	Description	Part #
RV1	CHIP SEMI RESISTOR 100KB	RSC-104ZN-JA
RV2	CHIP SEMI RESISTOR 100KB	RSC-104ZN-JA
RV3	CHIP SEMI RESISTOR 47KB	RSC-473ZN-JA
RV4	CHIP SEMI RESISTOR 10KB	RSC-103ZN-JA
RV5	CHIP SEMI RESISTOR 4.7KB	RSC-472ZN-JA
RV9	CHIP SEMI RESISTOR 4.7KB	RSC-472ZN-JA
RV12	CHIP SEMI RESISTOR 2.2KB	RSC-222ZN-JA
RV15	CHIP SEMI RESISTOR 100KB	RSC-104ZN-JA
RV17	CHIP SEMI RESISTOR 47KB	RSC-473ZN-JA

Cobra 150GTL DX

REF #	Description	Part #
R1	FILM CHIP RESISTOR 1K	R16-102AJ-AA
R2	FILM CHIP RESISTOR 220K	R16-224AJ-AA
R3	FILM CHIP RESISTOR 220K	R16-224AJ-AA
R4	FILM CHIP RESISTOR 100	R16-101AJ-AA
R5	FILM CHIP RESISTOR 100	R16-101AJ-AA
R6	FILM CHIP RESISTOR 100K	R16-104AJ-AA
R8	FILM CHIP RESISTOR 10K	R16-103AJ-AA
R9	FILM CHIP RESISTOR 6.8K	R16-682AJ-AA
R10	FILM CHIP RESISTOR 6.8K	R16-682AJ-AA
R11	FILM CHIP RESISTOR 100K	R16-104AJ-AA
R12	FILM CHIP RESISTOR 1M	R16-105AJ-AA
R13	FILM CHIP RESISTOR 10K	R16-103AJ-AA
R14	FILM CHIP RESISTOR 5.6K	R16-562AJ-AA
R15	FILM CHIP RESISTOR 100	R16-101AJ-AA
R16	FILM CHIP RESISTOR 470	R16-471AJ-AA
R17	FILM CHIP RESISTOR 1K	R16-102AJ-AA
R18	FILM CHIP RESISTOR 470K	R16-474AJ-AA
R19	FILM CHIP RESISTOR 22K	R16-223AJ-AA
R20	FILM CHIP RESISTOR 680	R16-681AJ-AA
R21	FILM CHIP RESISTOR 680	R16-681AJ-AA
R22	FILM CHIP RESISTOR 47K	R16-473AJ-AA
R23	FILM CHIP RESISTOR 270K	R16-274AJ-AA
R24	FILM CHIP RESISTOR 10K	R16-103AJ-AA
R26	FILM CHIP RESISTOR 47K	R16-473AJ-AA
R27	FILM CHIP RESISTOR 2.2K	R16-222AJ-AA
R28	FILM CHIP RESISTOR 1K	R16-102AJ-AA
R29	FILM CHIP RESISTOR 100	R16-101AJ-AA
R30	FILM CHIP RESISTOR 1K	R16-102AJ-AA
R31	FILM CHIP RESISTOR 8.2K	R16-822AJ-AA
R32	FILM CHIP RESISTOR 68K	R16-683AJ-AA
R33	FILM CHIP RESISTOR 22K	R16-223AJ-AA
R34	FILM CHIP RESISTOR 10K	R16-103AJ-AA
R36	FILM CHIP RESISTOR 680	R16-681AJ-AA
R37	FILM CHIP RESISTOR 100K	R16-104AJ-AA
R38	FILM CHIP RESISTOR 100K	R16-104AJ-AA
R39	FILM CHIP RESISTOR 100K	R16-104AJ-AA
R40	FILM CHIP RESISTOR 22K	R16-223AJ-AA
R41	FILM CHIP RESISTOR 82K	R16-823AJ-AA
R42	FILM CHIP RESISTOR 180K	R16-184AJ-AA
R43	FILM CHIP RESISTOR 47K	R16-473AJ-AA
R44	FILM CHIP RESISTOR 100K	R16-104AJ-AA
R45	FILM CHIP RESISTOR 680	R16-681AJ-AA
R46	FILM CHIP RESISTOR 270K	R16-274AJ-AA
R47	FILM CHIP RESISTOR 5.6M	R16-565AJ-AA
R48	FILM CHIP RESISTOR 1M	R16-105AJ-AA
R49	FILM CHIP RESISTOR 1K	R16-102AJ-AA
R51	FILM CHIP RESISTOR 100K	R16-104AJ-AA
R52	FILM CHIP RESISTOR 100K	R16-104AJ-AA
R53	FILM CHIP RESISTOR 39K	R16-393AJ-AA
R55	FILM CHIP RESISTOR 15K	R16-153AJ-AA
R57	FILM CHIP RESISTOR 100	R16-101AJ-AA

Cobra 150GTL DX

REF #	Description	Part #
R58	FILM CHIP RESISTOR 680K	R16-684AJ-AA
R59	FILM CHIP RESISTOR 2.2K	R16-222AJ-AA
R62	FILM CHIP RESISTOR 10K	R16-103AJ-AA
R64	FILM CHIP RESISTOR 6.8K	R16-682AJ-AA
R66	FILM CHIP RESISTOR 8.2K	R16-822AJ-AA
R67	FILM CHIP RESISTOR 3.3K	R16-332AJ-AA
R69	FILM CHIP RESISTOR 15K	R16-153AJ-AA
R71	FILM CHIP RESISTOR 6.8K	R16-682AJ-AA
R72	FILM CHIP RESISTOR 2.2K	R16-222AJ-AA
R73	FILM CHIP RESISTOR 2.2K	R16-222AJ-AA
R74	FILM CHIP RESISTOR 4.7K	R16-472AJ-AA
R75	FILM CHIP RESISTOR 10K	R16-103AJ-AA
R76	FILM CHIP RESISTOR 100K	R16-104AJ-AA
R79	FILM CHIP RESISTOR 6.8K	R16-682AJ-AA
R83	FILM CHIP RESISTOR 100	R16-101AJ-AA
R84	FILM CHIP RESISTOR 100K	R16-104AJ-AA
R85	FILM CHIP RESISTOR 100K	R16-104AJ-AA
R86	FILM CHIP RESISTOR 47	R16-470AJ-AA
R87	FILM CHIP RESISTOR 10K	R16-103AJ-AA
R88	FILM CHIP RESISTOR 82K	R16-823AJ-AA
R89	FILM CHIP RESISTOR 100	R16-101AJ-AA
R91	FILM CHIP RESISTOR 1K	R16-102AJ-AA
R92	FILM CHIP RESISTOR 100K	R16-104AJ-AA
R93	FILM CHIP RESISTOR 22K	R16-223AJ-AA
R96	FILM CHIP RESISTOR 47K	R16-473AJ-AA
R97	FILM CHIP RESISTOR 2.2	R16-022AJ-AA
R102	FILM CHIP RESISTOR 22K	R16-223AJ-AA
R112	FILM CHIP RESISTOR 100K	R16-104AJ-AA
R113	FILM CHIP RESISTOR 6.8K	R16-682AJ-AA
R115	FILM CHIP RESISTOR 2.2K	R16-222AJ-AA
R116	FILM CHIP RESISTOR 270	R16-271AJ-AA
R117	FILM CHIP RESISTOR 47K	R16-473AJ-AA
R118	FILM CHIP RESISTOR 68	R16-680AJ-AA
R121	FILM CHIP RESISTOR 33K	R16-333AJ-AA
R122	FILM CHIP RESISTOR 39K	R16-393AJ-AA
R123	FILM CHIP RESISTOR 47K	R16-473AJ-AA
R124	FILM CHIP RESISTOR 470K	R16-474AJ-AA
R125	FILM CHIP RESISTOR 82K	R16-823AJ-AA
R126	FILM CHIP RESISTOR 100K	R16-104AJ-AA
R127	FILM CHIP RESISTOR 47K	R16-473AJ-AA
R132	FILM CHIP RESISTOR 22K	R16-223AJ-AA
R133	FILM CHIP RESISTOR 2.2K	R16-222AJ-AA
R134	FILM CHIP RESISTOR 1K	R16-102AJ-AA
R138	FILM CHIP RESISTOR 1K	R16-102AJ-AA
R142	FILM CHIP RESISTOR 2.2K	R16-222AJ-AA
R143	FILM CHIP RESISTOR 22K	R16-223AJ-AA
R144	FILM CHIP RESISTOR 100K	R16-104AJ-AA
R146	FILM CHIP RESISTOR 2.2K	R16-222AJ-AA
R147	FILM CHIP RESISTOR 10K	R16-103AJ-AA
R148	FILM CHIP RESISTOR 6.8K	R16-682AJ-AA
R149	FILM CHIP RESISTOR 2.2K	R16-222AJ-AA
R151	FILM CHIP RESISTOR 680	R16-681AJ-AA
R152	FILM CHIP RESISTOR 220K	R16-224AJ-AA

Cobra 150GTL DX

REF #	Description	Part #
R153	FILM CHIP RESISTOR 1.5K	R16-152AJ-AA
R154	FILM CHIP RESISTOR 100	R16-101AJ-AA
R155	FILM CHIP RESISTOR 1K	R16-102AJ-AA
R156	FILM CHIP RESISTOR 10K	R16-103AJ-AA
R157	FILM CHIP RESISTOR 100	R16-101AJ-AA
R158	FILM CHIP RESISTOR 56	R16-560AJ-AA
R161	FILM CHIP RESISTOR 2.2K	R16-222AJ-AA
R163	FILM CHIP RESISTOR 3.3K	R16-332AJ-AA
R165	FILM CHIP RESISTOR 22K	R16-223AJ-AA
R166	FILM CHIP RESISTOR 100	R16-101AJ-AA
R167	FILM CHIP RESISTOR 22K	R16-223AJ-AA
R168	FILM CHIP RESISTOR 2.2K	R16-222AJ-AA
R169	FILM CHIP RESISTOR 2.2K	R16-222AJ-AA
R170	FILM CHIP RESISTOR 3.9K	R16-392AJ-AA
R171	FILM CHIP RESISTOR 47K	R16-473AJ-AA
R172	FILM CHIP RESISTOR 10K	R16-103AJ-AA
R173	FILM CHIP RESISTOR 47K	R16-473AJ-AA
R174	FILM CHIP RESISTOR 10K	R16-103AJ-AA
R175	FILM CHIP RESISTOR 2.2K	R16-222AJ-AA
R176	FILM CHIP RESISTOR 10K	R16-103AJ-AA
R177	FILM CHIP RESISTOR 22K	R16-223AJ-AA
R178	FILM CHIP RESISTOR 10K	R16-103AJ-AA
R179	FILM CHIP RESISTOR 220	R16-221AJ-AA
R181	FILM CHIP RESISTOR 22K	R16-223AJ-AA
R182	FILM CHIP RESISTOR 12K	R16-123AJ-AA
R183	FILM CHIP RESISTOR 4.7K	R16-472AJ-AA
R184	FILM CHIP RESISTOR 470	R16-471AJ-AA
R185	FILM CHIP RESISTOR 47K	R16-473AJ-AA
R186	FILM CHIP RESISTOR 4.7K	R16-472AJ-AA
R188	FILM CHIP RESISTOR 47K	R16-473AJ-AA
R191	FILM CHIP RESISTOR 4.7K	R16-472AJ-AA
R192	FILM CHIP RESISTOR 4.7K	R16-472AJ-AA
R195	FILM CHIP RESISTOR 22K	R16-223AJ-AA
R196	FILM CHIP RESISTOR 680K	R16-684AJ-AA
R197	FILM CHIP RESISTOR 47	R16-470AJ-AA
R199	FILM CHIP RESISTOR 1K	R16-102AJ-AA
R200	FILM CHIP RESISTOR 10K	R16-103AJ-AA
R201	FILM CHIP RESISTOR 1K	R16-102AJ-AA
R202	FILM CHIP RESISTOR 22K	R16-223AJ-AA
R203	FILM CHIP RESISTOR 27K	R16-273AJ-AA
R204	FILM CHIP RESISTOR 22K	R16-223AJ-AA
R205	FILM CHIP RESISTOR 22K	R16-223AJ-AA
R206	FILM CHIP RESISTOR 22K	R16-223AJ-AA
R209	FILM CHIP RESISTOR 100	R16-101AJ-AA
R211	FILM CHIP RESISTOR 22K	R16-223AJ-AA
R215	FILM CHIP RESISTOR 15K	R16-153AJ-AA
R216	FILM CHIP RESISTOR 10K	R16-103AJ-AA
R217	FILM CHIP RESISTOR 10K	R16-103AJ-AA
R218	FILM CHIP RESISTOR 15K	R16-153AJ-AA
R219	FILM CHIP RESISTOR 22	R16-220AJ-AA
R220	FILM CHIP RESISTOR 680	R16-681AJ-AA
R221	FILM CHIP RESISTOR 2.2K	R16-222AJ-AA
R222	FILM CHIP RESISTOR 10K	R16-103AJ-AA
R223	FILM CHIP RESISTOR 5.6K	R16-562AJ-AA

Cobra 150GTL DX

REF #	Description	Part #
R224	FILM CHIP RESISTOR 22K	R16-223AJ-AA
R226	FILM CHIP RESISTOR 1K	R16-102AJ-AA
R228	FILM CHIP RESISTOR 22	R16-220AJ-AA
R232	FILM CHIP RESISTOR 47K	R16-473AJ-AA
R233	FILM CHIP RESISTOR 1K	R16-102AJ-AA
R234	FILM CHIP RESISTOR 47K	R16-473AJ-AA
R235	FILM CHIP RESISTOR 15K	R16-153AJ-AA
R238	FILM CHIP RESISTOR 22	R16-220AJ-AA
R242	FILM CHIP RESISTOR 22K	R16-223AJ-AA
R244	FILM CHIP RESISTOR 22K	R16-223AJ-AA
R247	FILM CHIP RESISTOR 100	R16-101AJ-AA
R248	FILM CHIP RESISTOR 150	R16-151AJ-AA
R249	FILM CHIP RESISTOR 1.5K	R16-152AJ-AA
R250	FILM CHIP RESISTOR 330	R16-331AJ-AA
R252	FILM CHIP RESISTOR 6.8K	R16-682AJ-AA
R253	FILM CHIP RESISTOR 1K	R16-102AJ-AA
R254	FILM CHIP RESISTOR 18K	R16-183AJ-AA
R255	FILM CHIP RESISTOR 15K	R16-153AJ-AA
R256	FILM CHIP RESISTOR 10K	R16-103AJ-AA
R257	FILM CHIP RESISTOR 22K	R16-223AJ-AA
R258	FILM CHIP RESISTOR 100K	R16-104AJ-AA
R260	FILM CHIP RESISTOR 1K	R16-102AJ-AA
R264	FILM CHIP RESISTOR 1K	R16-102AJ-AA
R265	FILM CHIP RESISTOR 100	R16-101AJ-AA
R266	FILM CHIP RESISTOR 27K	R16-273AJ-AA
R267	FILM CHIP RESISTOR 1K	R16-102AJ-AA
R268	FILM CHIP RESISTOR 10K	R16-103AJ-AA
R272	FILM CHIP RESISTOR 1K	R16-102AJ-AA
R273	FILM CHIP RESISTOR 2.2K	R16-222AJ-AA
R274	FILM CHIP RESISTOR 10K	R16-103AJ-AA
R275	FILM CHIP RESISTOR 8.2K	R16-822AJ-AA
R276	FILM CHIP RESISTOR 1K	R16-102AJ-AA
R277	FILM CHIP RESISTOR 680	R16-681AJ-AA
R279	FIXED METAL OXIDE RESISTOR MOR 1W 10 5%	RXN-100GA-FA
R287	FILM CHIP RESISTOR 10K	R16-103AJ-AA
R288	FILM CHIP RESISTOR 10K	R16-103AJ-AA
R290	FIXED METAL OXIDE RESISTOR MORS 2W 3.9 5%	RXN-039GA-FA
R291	FILM CHIP RESISTOR 2.2K	R16-222AJ-AA
R295	FILM CHIP RESISTOR 10K	R16-103AJ-AA
R296	FILM CHIP RESISTOR 100	R16-101AJ-AA
R297	FILM CHIP RESISTOR 680	R16-681AJ-AA
R298	FILM CHIP RESISTOR 3.3K	R16-332AJ-AA
R299	FILM CHIP RESISTOR 100	R16-101AJ-AA
R302	FILM CHIP RESISTOR 10K	R16-103AJ-AA
R304	FILM CHIP RESISTOR 680	R16-681AJ-AA
R306	FILM CHIP RESISTOR 560	R16-561AJ-AA
R309	FILM CHIP RESISTOR 560	R16-561AJ-AA
R311	FILM CHIP RESISTOR 100	R16-101AJ-AA
R312	FILM CHIP RESISTOR 100K	R16-104AJ-AA
R313	FILM CHIP RESISTOR 100K	R16-104AJ-AA
R314	FILM CHIP RESISTOR 100K	R16-104AJ-AA
R315	FILM CHIP RESISTOR 100K	R16-104AJ-AA
R316	FILM CHIP RESISTOR 1.5K	R16-152AJ-AA
R317	FILM CHIP RESISTOR 330	R16-331AJ-AA

Cobra 150GTL DX

REF #	Description	Part #
R318	FILM CHIP RESISTOR 47	R16-470AJ-AA
R319	FILM CHIP RESISTOR 150	R16-151AJ-AA
R321	FILM CHIP RESISTOR 1.5K	R16-152AJ-AA
R322	FILM CHIP RESISTOR 330	R16-331AJ-AA
R323	FILM CHIP RESISTOR 10	R16-100AJ-AA
R325	FILM CHIP RESISTOR 10K	R16-103AJ-AA
R326	FILM CHIP RESISTOR 10K	R16-103AJ-AA
R327	FILM CHIP RESISTOR 10K	R16-103AJ-AA
R328	FILM CHIP RESISTOR 68K	R16-683AJ-AA
R329	FILM CHIP RESISTOR 68K	R16-683AJ-AA
R331	FIXED METAL OXIDE RESISTOR MORS 2W 4.7K 5%	RXN-472GA-FA
R335	FILM CHIP RESISTOR 10K	R16-103AJ-AA
R354	FILM CHIP RESISTOR 22K	R16-223AJ-AA
R406	FILM CHIP RESISTOR 1.5K	R16-152AJ-AA
R407	FILM CHIP RESISTOR 1.5K	R16-152AJ-AA
R408	FILM CHIP RESISTOR 1.5K	R16-152AJ-AA
R409	FILM CHIP RESISTOR 1.5K	R16-152AJ-AA
R410	FILM CHIP RESISTOR 1.5K	R16-152AJ-AA
R411	FILM CHIP RESISTOR 1.5K	R16-152AJ-AA
R412	FILM CHIP RESISTOR 1.5K	R16-152AJ-AA
R413	FILM CHIP RESISTOR 1.5K	R16-152AJ-AA
R414	FILM CHIP RESISTOR 1.5K	R16-152AJ-AA
R415	FILM CHIP RESISTOR 1.5K	R16-152AJ-AA
R416	FILM CHIP RESISTOR 1.5K	R16-152AJ-AA
R417	FILM CHIP RESISTOR 1.5K	R16-152AJ-AA
R418	FILM CHIP RESISTOR 1.5K	R16-152AJ-AA
R419	FILM CHIP RESISTOR 1.5K	R16-152AJ-AA
R420	FILM CHIP RESISTOR 1.5K	R16-152AJ-AA
R421	FILM CHIP RESISTOR 1.5K	R16-152AJ-AA
R422	FILM CHIP RESISTOR 100	R16-101AJ-AA
R423	FILM CHIP RESISTOR 100	R16-101AJ-AA
R424	FILM CHIP RESISTOR 22K	R16-223AJ-AA
R425	FILM CHIP RESISTOR 10K	R16-103AJ-AA
R426	FILM CHIP RESISTOR 10K	R16-103AJ-AA
R427	FILM CHIP RESISTOR 10K	R16-103AJ-AA
R428	FILM CHIP RESISTOR 10K	R16-103AJ-AA
R441	FILM CHIP RESISTOR 10K	R16-103AJ-AA
R442	FILM CHIP RESISTOR 100	R16-101AJ-AA
R449	FILM CHIP RESISTOR 15K	R16-153AJ-AA
R457	FILM CHIP RESISTOR 47K	R16-473AJ-AA
R458	FILM CHIP RESISTOR 47	R16-470AJ-AA
R500	FILM CHIP RESISTOR 15K	R16-153AJ-AA
R501	FILM CHIP RESISTOR 10K	R16-103AJ-AA
R505	FILM CHIP RESISTOR 4.7M	R16-475AJ-AA
R507	FILM CHIP RESISTOR 12K	R16-123AJ-AA
R508	FILM CHIP RESISTOR 4.7K	R16-472AJ-AA
R510	FILM CHIP RESISTOR 10K	R16-103AJ-AA
R512	FILM CHIP RESISTOR 2.2K	R16-222AJ-AA
R513	FILM CHIP RESISTOR 47	R16-470AJ-AA
R520	FILM CHIP RESISTOR 12K	R16-123AJ-AA

Cobra 150GTL DX

REF #	Description	Part #
R530	FILM CHIP RESISTOR 4.7K	R16-472AJ-AA
R531	FILM CHIP RESISTOR 15K	R16-153AJ-AA
R533	FILM CHIP RESISTOR 4.7K	R16-472AJ-AA
R536	FILM CHIP RESISTOR 4.7K	R16-472AJ-AA
R537	FILM CHIP RESISTOR 10K	R16-103AJ-AA
R538	FILM CHIP RESISTOR 100K	R16-104AJ-AA
R540	FILM CHIP RESISTOR 4.7K	R16-472AJ-AA
R541	FILM CHIP RESISTOR 4.7K	R16-472AJ-AA
R542	FILM CHIP RESISTOR 4.7K	R16-472AJ-AA
R547	FILM CHIP RESISTOR 4.7K	R16-472AJ-AA
R550	FILM CHIP RESISTOR 39K	R16-393AJ-AA
R561	FILM CHIP RESISTOR 470	R16-471AJ-AA
R598	FILM CHIP RESISTOR 47	R16-470AJ-AA
R600	FILM CHIP RESISTOR 100K	R16-104AJ-AA
R601	FILM CHIP RESISTOR 100K	R16-104AJ-AA
R602	FILM CHIP RESISTOR 100K	R16-104AJ-AA
R605	FILM CHIP RESISTOR 220K	R16-224AJ-AA
R606	FILM CHIP RESISTOR 1.2K	R16-122AJ-AA
R607	FILM CHIP RESISTOR 47K	R16-473AJ-AA
R608	FILM CHIP RESISTOR 330	R16-331AJ-AA
R609	FILM CHIP RESISTOR 1K	R16-102AJ-AA
R612	FILM CHIP RESISTOR 1K	R16-102AJ-AA
R613	FILM CHIP RESISTOR 2.2	R16-022AJ-AA
R614	FILM CHIP RESISTOR 1K	R16-102AJ-AA
R615	FILM CHIP RESISTOR 1K	R16-102AJ-AA
R616	FILM CHIP RESISTOR 10	R16-100AJ-AA
R617	FILM CHIP RESISTOR 10	R16-100AJ-AA
R661	FILM CHIP RESISTOR 68	R16-680AJ-AA
R662	FILM CHIP RESISTOR 22K	R16-223AJ-AA
R663	FILM CHIP RESISTOR 3.9K	R16-392AJ-AA
R664	FILM CHIP RESISTOR 680	R16-681AJ-AA
R666	FILM CHIP RESISTOR 2.2K	R16-222AJ-AA
R667	FILM CHIP RESISTOR 1K	R16-102AJ-AA
R672	FILM CHIP RESISTOR 5.6K	R16-562AJ-AA
R673	FILM CHIP RESISTOR 2.2	R16-022AJ-AA
R674	FILM CHIP RESISTOR 1.5K	R16-152AJ-AA
R675	FILM CHIP RESISTOR 10K	R16-103AJ-AA
R676	FILM CHIP RESISTOR 1K	R16-102AJ-AA
R677	FILM CHIP RESISTOR 2.2K	R16-222AJ-AA
R678	FILM CHIP RESISTOR 1K	R16-102AJ-AA
R680	FILM CHIP RESISTOR 2.2K	R16-222AJ-AA
R683	FILM CHIP RESISTOR 10K	R16-103AJ-AA
R686	FILM CHIP RESISTOR 10K	R16-103AJ-AA
R688	FILM CHIP RESISTOR 270	R16-271AJ-AA
R689	FILM CHIP RESISTOR 560	R16-561AJ-AA
R690	FILM CHIP RESISTOR 10	R16-100AJ-AA
R691	FILM CHIP RESISTOR 10	R16-100AJ-AA
R692	FILM CHIP RESISTOR 1	R16-010AJ-AA
R693	FILM CHIP RESISTOR 1	R16-010AJ-AA
R694	FILM CHIP RESISTOR 4.7K	R16-472AJ-AA
R695	FILM CHIP RESISTOR 18K	R16-183AJ-AA
R697	FILM CHIP RESISTOR 5.6K	R16-562AJ-AA
R698	FILM CHIP RESISTOR 47K	R16-473AJ-AA
R699	FILM CHIP RESISTOR 47K	R16-473AJ-AA

Cobra 150GTL DX

REF #	Description	Part #
R700	FILM CHIP RESISTOR 3.3K	R16-332AJ-AA
R702	FILM CHIP RESISTOR 10K	R16-103AJ-AA
R703	FILM CHIP RESISTOR 4.7K	R16-472AJ-AA
R711	FILM CHIP RESISTOR 47K	R16-473AJ-AA
R999	FILM CHIP RESISTOR 10K	R16-103AJ-AA

REF #	Description	Part #
J4	PHONE JACK SKJS-3518	JSP-353FM-SA
J5	PHONE JACK SKJS-3518	JSP-353FM-SA
	CONNECTER HEADER FP01-03R-2	NCH-03HD1-DA
	CONNECTER SOCKET ANT TC CH-239(D)	NCS-01HD1-TB
	PCB MAIN 234x186.8x1.6(T) 1/1 HALL	PFM-0089H-BA
	PCB MAIN 234x186.8x1.6(T) 1/1 HALL	PFM-0089I-BA

REF #	Description	Part #
	WIRE HARNESS UL1007 24AWG 55+7mm 2LINE 1H	WH2-4B062-FB
	HOUSING PH2.0mm 2P UL1007 24AWG 130+7(B,R)	WH2-4B137-FZ
	WIRE HARNESS UL1007 24AWG 175+7mm 2LINE 1H	WH2-4B182-FB
	WIRE HARNESS UL1007 24AWG 190mm 2LINE 2H	WH2-4B190-FA
	WIRE HARNESS UL1007 24AWG 205+7mm 2LINE 1H	WH2-4B212-FB
	WIRE HARNESS UL1007 24AWG 65mm 3LINE 2H	WH2-4C065-FA
	WIRE HARNESS UL1007 24AWG 130mm 3LINE 2H	WH2-4C130-FA
	WIRE HARNESS UL1007 24AWG 135mm 3LINE 2H	WH2-4C135-FA
	WIRE HARNESS UL1007 24AWG 110mm 6LINE 2H	WH2-4F110-FA
	WIRE HARNESS UL1007 24AWG 70mm 7LINE 2H	WH2-4G070-FA
	WIRE HARNESS UL1007 24AWG 80mm 8LINE 2H	WH2-4H080-FA
	WIRE HARNESS UL1007 24AWG 90mm 8LINE 2H	WH2-4H090-FA
	WIRE HARNESS UL1007 24AWG 55mm 12LINE 2H	WH2-4L055-FA
	WIRE UL1007 24AWG 7-120-7mm BLACK	WI2-4B134-FA
	WIRE UL1007 24AWG 7-215-7mm GREEN	WI2-4G229-FA

REF #	Description	Part #
	6P HOUSING ASSY FREQUENCY COUNTER	WI2-6Z170-EA
	STEREO SHIELD WIRE UL2547 28AWG 2C 5-10-95-10-5mm	WS2-8A125-FA
	WAFER PH2.0*2P WAFER	WW0-2VD02-FA
CON8	POWER CORD PLUG ASSY UL1015 14AWG RED/BLK 200mm 5mm	YPD-14200-FA
SP1	SPEAKER ES-100-A5310	ZSP-1ADG2-SC

Cobra 150GTL DX

AMR-00001-PKA PACKING ASSY

REF #	Description	Part #
	SCREW (+)MACHINE(BH) M3.0x6 Ni-PLATING	614-00001-AA
	PLUS SCREW (TH)5.0x12 1S TAPPING	640-00016-AA
	WASHER AW-3(IN TYPE) SPCC T=0.45 NI-PLATING	660-00005-AA
	WASHER BW-5(OUT TYPE) SPCC T=0.6	660-00006-AA
	MOUNTING BRACKET EGI T=1.6 BLACK SPRAY	740-00010-AA
	THUMB MOULD ABS 94HB BLACK #400(WITH INSERT)	830-00080-AA
	RUBBER BUSHING SILICONE RUBBER BLACK	881-00041-AA
	CABLE TIE PVC WHITE	902-00019-AA
	POLY BAG P.E 100x100	931-00100-DA
	POLY BAG P.E 100x300 T=0.05	931-00300-DA
	POLY BAG P.E 180x130 T=0.05	931-80130-DA
	AIR PLY BAG 360x260	933-60260-DA
	POLY BAG P.E 450x80 T=0.05	934-50080-DA
	POP CARD 250 ART PAPER	940-00091-AA
	WARNING SHEET 100 WOOD PAPER	940-00094-AA
	FRONT PAD DW1S T=7.5	942-00055-AA
	BACK PAD DW1S T=7.5	942-00057-AA
	PAD DW1S T=7.5 190x50	942-00061-AA
	OWNERS MANUAL 100 WOOD/80 WOOD PAPER	950-00176-AA
	GIFT BOX SW1S 450SC T=2.0	970-00090-AA
	INNER BOX DW1S T=2.0	971-00029-AA
	MIC BOX DW1S T=7.5	971-00031-AA
	OUT BOX DW1S T=7.5	980-00281-AA
	RANGE LABEL TRANSPARENT PVC STICKER	990-00418-AA